- Clear plastic cover for fast visual confirmation of fuse amp rating.
- Easy identification of blown fuses when LED indicating Auto fuses are installed.
- Gasket included with cover.

Part Number	No. Poles	Max Amps Per Block
00610K	4 Pole	80A
00600K	6 Pole	100A
00590K	8 Pole	135A

Voltage: 32V

Input Terminal Rating: 20A max. per circuit.

Body: Black PA66 GF30

Cover: Transparent cover with gasket. Material PA12.

Terminals: Lateral connections, 6.35mm (1/4") QC terminals.

Kit Contents: Cover, base & QC terminals.

Mounting: M5 screw Pack Size: 1, 10, 100, 500

Notes: Each fuse branch is independently powered.

Fuses are not included. **Approvals:** [RoHS]



I/4" Quick Connects


Mounting Diagram

Ø5.5 65 ++5


00610K 4 Way Lateral Kit



Dimensions in MM




Mounting Diagram




00600K 6 Way Lateral Kit






Mounting Diagram



00590K 8 Way Lateral Kit







Email: info@prolecproducts.com Web: www.prolecproducts.com